







Hisaver Hibay V3 Luminaire

RX Lighting Hisaver Stirrup Mount

Physical Dimensions:





REXHBPCREFDIF




| Part | Qty |
|--------------|-----|
| Reflector | 1 |
| Lens Base | 1 |
| Screw Ø4x12 | 3 |
| Screw Ø3.5x8 | 1 |


Please check all parts are included in the kit before assembly begins.




Install the diffuser body to the Hibay using the 3 screws. M4 x 12mm long






Align the lower diffuser cover by matching the 3 twist clips and the lock screw hole positions



Push the cover into the body and then rotate in a clockwise direction until the clips lock in place. Check the lock screw holes are aligned and then insert the M3.5x8 screw and gently tighten. 0.8N.m max



REXHB90ALIREF



| | | |
|------|--------------|-------|
| L | brown | black |
| N | blue | white |
| ⊕GND | yellow/green | green |

| Dimmable | |
|------------|------------------------------------|
| DIM+/DA1 | purple or purple or blue or brown |
| DIM-/DA2 | gray or pink or white or blue |
| DIM+/DA1 | purple or purple or purple |
| DIM-/DA2 | gray or pink or gray |
| Aux 12Vdc+ | pink or black/white or black/white |



Warning! Do not wire dim cord to high voltage (230V) or luminaire and / or dim function will fail.

• If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.


Hisaver Hibay V3 Luminaire

Installation Instructions


REXHISLED200WV3 - SUSPENDED

REXHBSCHAIN1.5M - Suspension Chain - Stainless Steel Welded Link 1.5m Long


If Suspension Wire or alternative chain is used it must be able to carry 6.5KG Minimum load




REXHISLED200WV3
Physical Dimensions;



Rotatable lens




W-Wide beam
M-Medium beam
N-Narrow beam



Adjustable power

CAUTION:
Ensure power is off at the luminaire before adjusting the DIP switch. Do not use a metal tool to adjust the DIP switch. Please adjust the switch gently.




ON
●
●
●
OFF


| 1 | 2 | 3 | Power |
|---|---|---|-------|
| ● | ○ | ○ | 200W |
| ○ | ● | ○ | 150W |
| ○ | ○ | ● | 120W |
| ○ | ○ | ○ | 100W |

Max.200W

REXHISENSORV3 - Motion Sensor
REXHISREMOTEV3 - Remote Control for sensor setting
REXHISCASMMOD - Casambi Ready Wireless Control Module



REXHISCASMMOD
OR
REXHISENSORV3



Suspension Mount

⚠ Make sure the screws are tightened

