

Ecoline Mini 8 766/7 9.. ..0
 Anbauleuchte 8 766/7 0.. ..0
 Luminaire 8 766/7 1.. ..0
 8 766/7 2.. ..0
 8 766/7 3.. ..0

Schutzart – Protection IP 65
 Schutzklasse – Safety Class I



MONTAGE
 ANLEITUNG
 MOUNTING
 INSTRUCTIONS




WILLY MEYER & SOHN GMBH & CO.KG
 LICHTTECHNISCHE SPEZIALFARIK
 Stemmessiepenener Weg 5 • D-58675 Hemer

LED-Anbauleuchte

MONTAGEHINWEISE

Anschluss der Leuchte nach VDE 0100.
 Anbauleuchte für ungeschützte Anlagen.
 Leuchte ist geeignet für Montage auf normal entflammaren Baustoffen.
 Die Leuchte ist **nicht** zu öffnen.
 Der elektrische Anschluss erfolgt über die 1m lange 3- bzw. 5-adrige Zuleitung.
 Im Falle einer Beschädigung muss die Leuchte eingeschickt und vom Hersteller repariert/ausgetauscht werden.
 Befestigungswinkel / Wandausleger auf dem Montagegrund befestigen.
 Elektrischen Anschluss vornehmen.


Das Glas besteht aus Polycarbonat.



Die Leuchte darf nur mit ihrer vollständigen Schutzabdeckung betrieben werden.

Max. Anzahl Leuchten an einem
 Sicherungsautomat B16 : 50 Stück
 Einschaltstrom : 5A 50µsec

In Strahlrichtung den Mindestabstand zur angestrahlten Fläche einhalten!




Die in dieser Leuchte eingebaute Lichtquelle darf nur durch den Hersteller ersetzt werden.



LED-Luminaire

MOUNTING INSTRUCTIONS


Connect the light fitting in compliance with prevailing regulations in your country.
 Luminaire for non-protected outdoor installation.
 Light fitting is suitable for mounting on normal inflammable surfaces.
 The luminaire **cannot** be opened. Electrical connection must be made using the 1 metre of 3 or 5 core cable which is attached to the luminaire. If the luminaire gets damaged or ceases to function, it must be returned to the manufacturer to be repaired or exchanged. Fix the mounting flange or wall arm to the surface on which luminaire is to be mounted. Make electrical connection.
 The cover is made of polycarbonate.



The light fitting may be operated only if all protective covers are in place.

Max. Number of fittings per
 circuit breaker B16 : 50 pieces
 Inrush current : 5A 50µsec

Ensure that the minimum spacing between luminaire and illuminated surface is observed.



The light source contained in this luminaire shall only be replaced by the manufacturer.



Leuchte/ type /	Gewicht/ weight /	Windangriffsfläche/ Projected area /	LED-Leistung / wattage / puissance	Gesamtlänge L1 in mm/ overall length / longueur totale	Befestigungsabstand L2 in mm/ distance between fixing point / distance de fixation
8 766/7 9..	1,1 Kg	0,017 m ²	3 x 1,7 W (5,1 W)	444	407
8 766/7 0..	1,5 Kg	0,025 m ²	6 x 1,7 W (10,2 W)	668	631
8 766/7 1..	2,1 Kg	0,037 m ²	9 x 1,7 W (15,3 W)	962	925
8 766/7 2..	2,5 Kg	0,048 m ²	12 x 1,7 W (20,4 W)	1256	1219
8 766/7 3..	3,0 Kg	0,059 m ²	15 x 1,7 W (25,5 W)	1550	1513

